

MYLS-3C

Stand-Alone Handy Flash IC Writer



Introduction

MYLS-3C, a compact, user friendly handy stand-alone writer that is specially designed for FLASH EPROM series. It can be powered by power adaptor or batteries. Together with the slave ZIF socket, MYLS-3C is able to process programming without PC connection. It's an economic tool for programming FLASH memory.



Standard Accessories

- Main unit.....x1
- DC 12V/500mA power adaptor.....x1
- USB cable.....x1
- CD.....x1
- (Driver and user manual are included)

Optional Accessories

- PLCC-32/TSOP-32/VSOP-32 adaptors

Features

- Stand-alone Flash programmer.
- Light, short, thin, tiny, portable and usable with batteries.
- Copy master IC in stand-alone mode.
- Two operation modes: Stand-alone and PC-link mode.
- User friendly graphic operational interface.
- Able to set programming parameters, such as program algorithm, Vpp, pulse width, etc.

Specification

User Interface	16 x 2 character LCD
Power	DC 12V/500mA
Dimension	16cm x 11cm x 4.5cm
Weight	500g
Operating Altitude	up to 5000m
Operating Humidity	90% (non-condensing)
Temperature	+5°C ~ +45°C
Communication	USB 1.1

PC System Requirement

Operating System	Windows 98/ME/2000/XP	Memory	128MB RAM and above
Processor	Pentium III and above	Hard Disk	30MB and above

File Type Supported

- Binary / Machine Code、intel HEX、Motorola HEX、

Device Supported

27CXX 27C64 27C128 27C256 27C512 27C010 27C020 27C040 27C080	V29C51004B V29C51004T V29C31004B V29C31004T
AMD AM29F010 AM29F010A AM29F010B AM29F002B AM29F002T AM29F002NB AM29F002NT AM29F002B8 AM29F002NB8 AM29F002NB1 AM29F040 AM29F040B AM29LV010B AM29LV001B8	MX29F001B MX29F001T MX29F002B MX29F002NB MX29F040 MX29F040B MX29LV004B MX26C1000B MX26C2000
AMIC A29001U A29001T A29001U A29001T A29001U A29001T A29001U A29001T A29002U A29002T	PERFECT PDT29F010 PE29F002N
ATMEL AT49F512 AT49F010 AT49F001 AT49F001N AT49F001T AT49F001NT AT49F020 AT49F002 AT49F002N AT49F002NT AT49F040 AT49F040T AT49LV001 AT49LV001T AT49LV002 AT49LV002T AT49LV002N AT49LV002NT AT49LV040 AT49LV040T AT49BV001 AT49BV001T AT49BV002 AT49BV002T AT49BV002N AT49BV002NT AT29C512 AT29C010 AT29C010A AT29C020 AT29C040 AT29C040A AT29LV512 AT29LV010A AT29LV020 AT29LV020A AT29BV010A AT29BV020 AT28C010 AT28C040	PM29F002B PM29F002T PM29F004B PM29F004T PM29LV002B PM29LV002T PM29LV004B PM29LV004T ST M29F010B M29F002B M29F002T M29F002NT M29F040B M29W010B M29W022B M29W022BT M29W040 M29W040B M28F101 M28F201 SST SST39SF512 SST39SF010 SST39SF010A SST39SF020 SST39SF020A SST39SF040 SST39LF512 SST39LF010 SST39VF020 SST39VF040 SST29EE512 SST29EE512A SST29EE010 SST29EE011 SST29EE020 SST29LE010A SST29LE020 SST29LE020A SST29VE512 SST29VE512A SST29VE010 SST29VE010A SST29VE020 SST29VE020A SST28SF040 SST28SF040A SST28LF040 SST28VF040 SST28VF040A SST27SF256 SST27SF512 SST27VF010 SST27VF020 SST27VF040 SST27VF040A SST37VF010 SST37VF020 SST37VF040
BRILIGHT BM29F040	SYNCHOS F29C51001B F29C51001T F29C51002B F29C51002T F29C51004B F29C51004T F29C31004B F29C31004T
EON EN29F002B EN29F002NB EN29F002T EN29F002NT	WINBOND W49F020 W49F002A W49F002B W49V020 W49V002A W49V002B W29C010 W29C011A W29C020 W29C020C W29C040 W29EE512 W29EE010 W29EE011 W29EE020 W29EE040 W27C256 W27C257 W27C512 W27C010 W27C020 W27E256 W27E257 W27E512 W27E010 W27E020 W27E040 W27F257 W27F512 W27F5010
FUJITSU MBM29F010 MBM29F002B MBM29F002T MBM29F040 MBM29F040A MBM29F040C	
HYUNDAI HY29F002B HY29F002T HY29F040 HY29F040A	
INT IM29F001T IM29F002T	
MEGAWIN MM29F040E MM29LV040E	
MOSEL V29C51001B V29C51001T V29C51002B V29C51002T	